

Bently Nevada 990-04-50-02-01 Manual

Brand	Bently Nevada
Product Series	991&990
Product Type	990 Vibration Transmitter

Description

Manufacturer : Bently Nevada

Product No. : 990-04-50-02-01

Product Type : 990 Vibration Transmitter

Made in U.S.A

Full-scale Option : 0 4 - 0.4 mils pp (0-100 μ m pp)

System Length Option : 5 0 - 5.0 metres (16.4 feet)

Mounting Option : 02 Bulkhead screws

Agency Approval Option : 01 CSA Division 2

Input : Accepts 1 non-contacting 3300 NSv Proximity Probe and extension cable.

Power : Requires +12 to +35 Vdc input at the transmitter terminal.

Maximum Loop Resistance : 1,000 Ω including cable at 35 Vdc.

Current Limiting : 23 mA typical.

Transmitter
weight 0.43 kg (0.9 lbm).

Input
Accepts 1 non-contacting 3300
NSv Proximity Probe and
extension cable.
Power Requires +12 to +35 Vdc input at
the transmitter terminal.
4 to 20 mA
signal output
4 to 20 mAdc over specified fullscale range in 2-wire
configuration.

4 to 20 mA loop

accuracy

Within $\pm 1.5\%$ over specified fullscale range. Accuracy is rated

from the TEST signal input to the

voltage measured across a $250\ \Omega$

loop resistance. The $\pm 1.5\%$ error is

in addition to the Prox Out

Incremental Scale Factor.

Probe gap

Probe must be gapped between

0.5 and 1.75 mm (20 and 55 mils)

from target to ensure full scale

range.

Maximum loop

resistance $1,000\ \Omega$ including cable at 35 Vdc.

Current limiting 23 mA typical.

Zero and span

Non-interacting external

adjustments.

NOT OK/signal

defeat

Signal output will go to less than

3.6 mA within $100\ \mu\text{s}$ after a Not

OK condition occurs. Signal

output is restored within 2-3

seconds after the Not OK

condition is removed.

Frequency

response

5 Hz to 6,000 Hz $\pm 0, 3\ \text{dB}$.

Minimum

target size 9.5 mm (0.375 in) diameter.

Leadwire

length

Maximum for Proximity Sensor

Output (BNC connector),

maximum cable distance is 3

meters (10 feet).

NonHazardous,

Zone 2 or Div 2

Hazardous

area locations

Power Supply: 28 V

www.AutoDCSTech.com